

(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11)

EP 0 765 546 B1

(12)

EUROPEAN PATENT SPECIFICATION

(45) Date of publication and mention
of the grant of the patent:
09.12.1998 Bulletin 1998/50

(21) Application number: **95921938.7**

(22) Date of filing: **16.06.1995**

(51) Int Cl.⁶: **H04B 10/10**

(86) International application number:
PCT/GB95/01410

(87) International publication number:
WO 95/34963 (21.12.1995 Gazette 1995/54)

(54) **FREE SPACE COMMUNICATIONS SYSTEM EMPLOYING LINE OF SIGHT RADIATION**

LEITUNGSUNGEBUNDENES KOMMUNIKATIONSSYSTEM UNTER VERWENDUNG VON
SICHTLINIENSTRAHLUNG

SYSTEME DE COMMUNICATION EN ESPACE LIBRE UTILISANT UNE RADIATION TRANSMISE
EN LIGNE DE VISEE

(84) Designated Contracting States:
AT BE CH DE DK ES FR GB IE IT LI NL PT SE

(30) Priority: **16.06.1994 GB 9412031**

(43) Date of publication of application:
02.04.1997 Bulletin 1997/14

(73) Proprietor: **IML Ltd.**
Haslemere, Surrey GU27 2QA (GB)

(72) Inventor: **KNOWLES, Michael**
Surrey GU27 2QA (GB)

(74) Representative: **Bubb, Antony John Allen et al**
Chancery House
Chancery Lane
London WC2A 1QU (GB)

(56) References cited:
WO-A-91/07028 **DE-A- 2 431 837**
US-A- 5 089 346

EP 0 765 546 B1

Note: Within nine months from the publication of the mention of the grant of the European patent, any person may give notice to the European Patent Office of opposition to the European patent granted. Notice of opposition shall be filed in a written reasoned statement. It shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

Description

This invention concerns signalling devices employing line of sight radiation, and more especially, but not exclusively, to infra red transmitters and receivers of the kind that are designed to communicate using coded signals.

Such devices have particular application in circumstances where relatively short range line of sight communication is appropriate, and avoid disadvantages inherent in, for example, radio communication or the use of cables. They do have the disadvantage, however, that signal communication is interrupted when there is no direct line of sight between transmitter and receiver. Where relatively short range communication is involved, it has been proposed to overcome the latter disadvantage by providing infra red reflectors or repeaters to enable transmission via an indirect path. This presupposes however that the path or paths of transmission can be planned in advance and does not allow for possible random interruption of signal paths.

It is accordingly an object of the present invention to provide an improved means of line of sight signal transmission that is less susceptible to failure as a result of random blockage of signal paths and that is therefore usable in systems of a kind that has hitherto required the use of radio or direct cabling.

One known communication system, for example, makes use of a communication link for polling a number of hand held keypad devices used in gathering opinions from delegates at meetings.

At such a meeting, each delegate is equipped with a hand held keypad. The presenter displays a question on a video screen and the delegates enter their response on their keypad. Each keypad responds to a different address and as the controlling computer polls the keypad addresses they each return their delegate's response.

Such a system uses serial bi-directional communications over cables. Most conferences are held in venues which do not provide group response systems so that such a system would be hired in for the duration and installed on a temporary basis. The installation of such a system is labour intensive in view of the requirement for the provision of cabling, and thus a system that avoided the use of cables would provide a significant advance on the state of the art.

DE-A-2 431 937 discloses the use of devices based on radiation (i.e., non-cabled) in the environment of an audience polling system, wherein "line-of-sight" radiation is employed in conference rooms or the like. However, those devices cannot be used both as transmitters and as repeaters.

WO-A-91 07028 discloses an arrangement wherein a plurality of repeaters are arranged to provide line-of-sight communication between a transmitter and a receiver located within a given area. The repeaters act as passive repeaters of pulses of radiated energy, and are

arranged to incorporate a lock-out period wherein each repeater is disabled for a predetermined period of time following its response to a received pulse. Such an arrangement enables line-of-sight propagation of a pulsed signal via a plurality of possible propagation paths, without ambiguity caused by a repeater responding to a pulse that it has already transmitted. In such an arrangement, however, the repeaters, which are intended to be arranged at a fixed spacing, act merely passively to propagate radiation between dedicated transmitters and receivers.

US-A-5 099346 describes a system for the propagation of line-of-sight radiation between devices that can receive and transmit in alternative modes in which they act either as originating transmitters, or as passive repeaters of a signal transmitted by another device. In this system, however, for a device to act as a repeater it is necessary for a predetermined signal path to be established so that the repetition of signals is via a defined path through a network. For the device to operate, a relatively complicated communications protocol is therefore required.

The present invention provides a polling system employing line-of-sight radiation, and a device operating in both a transmitting mode and a repeating mode for use therein, as respectively set out in claim 5 and claim 1.

Further preferred features of the invention will become apparent from the dependent claims taken in conjunction with the following description.

The invention is illustrated by way of example in the accompanying drawings, in which:

Figure 1 is a plan view illustrating one arrangement of signal transmission system according to the invention,

Figure 2 is a timing diagram illustrating the operation of system as shown in Fig. 1.

Figure 3 is a circuit diagram of a repeater of the system of Fig. 1, and

Figure 4 is a plan view in diagrammatic form of a hand held keypad/repeater unit.

Figure 1 shows a typical seating plan of a room containing a polling system of the kind described above and embodying a signal transmission system according to the invention utilising infra red links to eliminate the cabling of the known system. Keypads are shown in four regions labelled B, C, D, and E. A transceiver A for polling the keypads is shown in the top right hand corner of the room and the regions indicate the general progression of the communications using the proposed repeater method. The polling command and keypad address first emanate from A and act directly with region B. Region B repeats the signals to region C and so on to region D and then region E. The keypad that is being polled, lets say in region E then radiates its signal to region D which repeats it to region C and so on back to the transceiver A.

The key factors to be considered, to make this

method successful, are feedback loops and propagation delays.

Figure 2 shows a timing chart with the transceiver signal A being successively delayed through each region B1 in region B, C1 in region C, D1 in region D, E1 in region E at times t1, t2, t3, t4 and t5.

To prevent feedback loops, each repeater has a lockout period B2, C2, D2, E2 which is initiated by a received pulse. Looking at figure 2 keypads in region B could be retriggered by keypads in region D. To prevent this the receiving circuit in B is disabled for the lockout period B2.

This strategy works provided that there are not so many propagation stages that keypads could be producing pulses after the lockout period as shown by X1 in figure 2.

However as such a key pad would be out of range of keypads that have ended their lockout period this would not be a problem. The lockout period may, for example, be only 4 to 10 times the propagation delay.

Figure 3 shows how the repeater is implemented using standard electronics techniques.

The received signal at the diode detector A is amplified and differentiated B. The signal is passed through a comparator C with its threshold C1 set above noise levels. The output pulse is then retimed by monostable D to produce a signal for repetition. The lockout monostable E is also triggered by monostable D. Monostable E disables monostable D during the lockout period.

The lockout period is less than or at most equal to the interval between consecutive pulses of a coded signal. As shown in Fig. 2 the lockout period B2 ends at time t6 before the next pulse of transceiver signal A at time t7. Each keypad thus recognises the individual pulses originating from the transceiver whilst ignoring repetitions of the same pulse.

Whilst repeating the transmitted pulses each keypad also decodes the signal via the microprocessor shown in Fig. 3 to determine whether its own address has been transmitted and it should transmit a response to the poll. Such a response includes data input manually via the keypad and stored by the microprocessor as is conventional in the known systems referred to above.

When a keypad is transmitting its delegate's response it changes from repeater mode to originator mode using the mode control line and mode switch F. After it has completed its transmission the keypad returns to repeater mode.

In the illustrated embodiment the normal non-return-to-zero (NRZ) serial data format of the microprocessor is converted to return-to-zero (RZ) serial data format for transmission. This improves the integrity of the signal once it is converted into pulses. The RZ signal is likewise converted to NRZ at the input to the microprocessor.

Advantageously each keypad has IR detectors and emitters on its sides as well as the front edge. Such an arrangement is shown in Fig. 4, wherein IR detectors

are illustrated at 10 and emitters at 11. This allows the signal to pass across a row of delegates sitting next to each other. In addition to keys 14 for manual input, the keypad may also have a microphone 12 which transmits using infra red and preferably also the repeater method. In the latter case the mode switch F will be set to originator mode upon use of the microphone, for example, in response to actuation of a transmission button 13 associated with the microphone. The keypad is held up to the speaker's mouth when it is being used, hence the importance of sidelooking transceivers which retain their general sideways view when the keypad is held like this. It will be appreciated that alternative means may be provided for the reception of microphone signals, such as dedicated IR receivers at the ends of each row of seating.

Claims

1. A device for use in an audience polling system, comprising a portable hand-held unit including a keypad (14) for the entry of data, a microprocessor, a radiation transmitting means (11), and a radiation receiving means (10), the said microprocessor being programmed to respond to a pulse-modulated signal received by said radiation receiving means (10) and to cause a pulse-modulated signal to be transmitted by said radiation transmitting means (11), the pulse modulation in each case comprising signal pulses spaced by at least a predetermined interval of time that is greater than a predetermined multiple of the duration of a signal pulse, said device further comprising a mode switching means (F) controlled by said microprocessor for setting said device either in a repeating mode in which pulses received by said radiation receiving means (10) are caused to be repeated by said radiation transmitting means (11) or in a transmitting mode in which data entered via the keypad (14) and stored by the microprocessor is caused to be transmitted as an original pulse-modulated signal and any received pulses are ignored, and the arrangement being such that the microprocessor is arranged to store a unique address identifying the particular device, and that when in the repeating mode, upon receipt of each pulse of a said signal, the receiving means is disabled for a predetermined period of time greater than a multiple of the duration of the pulse transmitted by said transmitting means (11) and less than said predetermined interval, whereas, upon receipt of a polling signal transmitted by a polling transceiver and containing said unique address, said polling signal is recognised by said microprocessor and the said mode switching means (F) is actuated to set the device in said transmitting mode in order to return an answer signal to said polling transceiver.

2. A device according to Claim 1, including a microphone (15) for generating an original signal, and means arranged to set said device as a transmitter of the microphone signal when said microphone is in use.
3. A device according to Claim 2, wherein said radiation receiving and transmitting means comprise a plurality of radiation receiving (10) and transmitting (11) elements at least some of which are located on one or more side edges of the device so that radiation can be transmitted sideways along a row of such devices when held in an upright position for use as a microphone.
4. A device according to Claim 3 further comprising said transmitting and/or receiving elements along a front edge of the device, when laid at rest.
5. An audience polling system comprising a plurality of devices as claimed in any one of Claims 1 to 4 and a transceiver (A, Fig. 1) arranged to poll said devices by transmitting for each device a pulse-modulated signal containing the unique address thereof and storing the signal returned by each respective device, the arrangement being such that the said plurality of devices are arranged in a given area to provide a plurality of line-of-sight radiation propagation paths from said transceiver (A) via a plurality of said devices acting as repeaters to further ones of said devices at boundaries of said area and that the longest propagation path and the response time of each device when acting as a repeater is such that all repeaters in said longest path will have responded to a given pulse from said transceiver within the said predetermined period of time during which the receiving means is disabled.

Patentansprüche

1. Vorrichtung zur Verwendung in einem Auditoriums-Abstimmungssystem, mit einer tragbaren Einheit, die in der Hand gehalten werden kann und ein Tastenfeld (14) zur Eingabe von Daten, einen Mikroprozessor, eine Strahlungssende-Einrichtung (11) sowie eine Strahlungsempfangs-Einrichtung (10) umfaßt, wobei der Mikroprozessor programmiert ist, um auf ein pulsmoduliertes Signal anzusprechen, welches von der Strahlungsempfangs-Einrichtung (10) empfangen wird, und zu bewirken, daß ein pulsmoduliertes Signal von der Strahlungssende-Einrichtung (11) gesendet wird, wobei die Pulsmodulation in jedem Fall Signalepulse umfaßt, die mindestens um ein vorbestimmtes Zeitintervall voneinander getrennt sind, das größer ist als ein vorbestimmtes Vielfaches der Dauer eines Signalepulses, wobei die Vorrichtung ferner eine Modus-

umschalt-Einrichtung (F) aufweist, die von dem Mikroprozessor gesteuert wird, um die Vorrichtung entweder in einen Wiederholmodus, in welchem von der Strahlungsempfangs-Einrichtung (10) empfangene Pulse von der Strahlungssende-Einrichtung (11) wiederholt werden, oder in einen Sendemodus versetzen, in welchem mittels des Tastenfeldes (14) eingegebene und mittels des Mikroprozessors gespeicherte Daten als ein original-pulsmoduliertes Signal gesendet werden und alle empfangene Pulse ignoriert werden, wobei der Mikroprozessor ausgelegt ist, um eine einzige Adresse zu speichern, welche die spezielle Vorrichtung identifiziert, und wobei in dem Wiederholmodus nach dem Empfangen eines jeden Pulses eines solchen Signals die Empfangseinrichtung für eine vorbestimmte Zeitdauer gesperrt wird, die größer als ein Vielfaches der Dauer des von der Sende-Einrichtung (11) gesendeten Pulses und kleiner als das vorbestimmte Intervall ist, wohingegen nach dem Empfang eines Abstimmungssignals, welches von einem Abstimmungs-Sende-Empfänger gesendet wurde und die einzige Adresse enthält, das Abstimmungssignal von dem Mikroprozessor erkannt wird und die Modusumschalt-Einrichtung (F) betätigt wird, um die Vorrichtung in den Sendemodus zu versetzen, um ein Antwortsignal an den Abstimmungs-Sende-Empfänger zurückzusenden.

2. Vorrichtung gemäß Anspruch 1, umfassend ein Mikrophon (15) zum Erzeugen eines Originalsignals und eine Anordnung zum Einsetzen der Vorrichtung als Sender für das Mikrophonsignal, wenn das Mikrophon in Gebrauch ist.
3. Vorrichtung gemäß Anspruch 2, wobei die Strahlungsempfangs- und die Strahlungssende-Einrichtung eine Mehrzahl von Strahlungsempfangs- (10) und -sende-(11) Elemente aufweisen, von denen mindestens einige auf einer oder mehreren Seitenflächen der Vorrichtung angeordnet sind, so daß Strahlung seitwärts entlang einer Reihe solcher Vorrichtungen übertragen werden kann, wenn diese in senkrechter Stellung für die Verwendung als Mikrophon gehalten werden.
4. Vorrichtung gemäß Anspruch 3, ferner versehen mit Sende- und/oder Empfangs-Elementen entlang einer Stirnseite der Vorrichtung, wenn diese in Nichtbenutzung abgelegt ist.
5. Auditoriums-Abstimmungssystem mit einer Mehrzahl von Vorrichtungen gemäß einem der Ansprüche 1 bis 4 und einem Sende-Empfänger (A, Fig. 1), der vorgesehen ist, um die Vorrichtungen mittels Sendens eines pulsmodulierten Signals, das die einzige Adresse der jeweiligen Vorrichtung enthält, an jede Vorrichtung und Speichern des von jeder

Vorrichtung empfangenen Signals abzufragen, wobei die Mehrzahl von Vorrichtungen in einem vorgegebenen Bereich angeordnet sind, um für eine Mehrzahl von Sichtlinien-Strahlungs-Ausbreitungswegen von dem Sende-Empfänger (A) zu sorgen, wobei eine Mehrzahl der Vorrichtungen als Wiederholer-Einrichtungen für weitere der Vorrichtungen an den Grenzen des Bereichs wirken, sowie daß der längste Ausbreitungsweg und die Ansprechzeit einer jeden Vorrichtung, wenn sie als Wiederholer-Einrichtung wirkt, derart ist, daß alle Wiederholer-Einrichtungen in dem längsten Weg auf einen vorgegebenen Puls von dem Sende-Empfänger innerhalb der vorgegebenen Zeitdauer ansprechen, während welcher die Empfangs-Einrichtung gesperrt ist.

Revendications

1. Dispositif destiné à être utilisé dans un système d'interrogation d'une assistance, comprenant une unité à main portable comprenant un clavier (14) pour l'entrée de données, un microprocesseur, des moyens d'émission d'un rayonnement (11) et des moyens de réception du rayonnement (10), ledit microprocesseur étant programmé pour répondre à un signal modulé en impulsion reçu par lesdits moyens de réception de rayonnement (10) et pour faire qu'un signal modulé en impulsion soit émis par lesdits moyens d'émission d'un rayonnement (11), la modulation en impulsion comprenant dans chaque cas des impulsions de signaux espacées d'au moins un intervalle de temps prédéterminé supérieur à un multiple prédéterminé de la durée d'une impulsion de signal, ledit dispositif comprenant en outre des moyens de commutation de mode (F) commandés par ledit microprocesseur pour placer ledit dispositif, soit dans un mode de répétition dans lequel les impulsions reçues par lesdits moyens de réception d'un rayonnement (10) sont amenées à être répétées par lesdits moyens d'émission de rayonnement (11), soit dans un mode d'émission dans lequel les données entrées par l'intermédiaire du clavier (14) et stockées par le microprocesseur sont amenées à être émises en tant que signal original modulé en impulsion et dans lequel toutes les impulsions reçues sont ignorées, l'agencement étant tel que le microprocesseur est agencé pour stocker une adresse unique identifiant le dispositif particulier et que, lorsqu'ils sont dans le mode de répétition, lors de la réception de chaque impulsion d'un tel signal, les moyens de réception sont rendus inactifs pendant une période de temps prédéterminée supérieure à un multiple de la durée de l'impulsion émise par lesdits moyens d'émission (11) et inférieure audit intervalle prédéterminé, tandis que, lors de la réception d'un signal d'interrogation émis

par un émetteur-récepteur d'interrogation et contenant ladite adresse unique, ledit signal d'interrogation est reconnu par ledit microprocesseur et lesdits moyens de commutation de mode (F) sont actionnés pour placer le dispositif dans ledit mode d'émission afin de renvoyer un signal de réponse audit émetteur-récepteur d'interrogation.

2. Dispositif selon la revendication 1, comprenant un microphone (15) pour produire un signal original et des moyens agencés pour placer ledit dispositif en tant qu'émetteur du signal du microphone lorsque ledit microphone est en service.
3. Dispositif selon la revendication 2, dans lequel lesdits moyens de réception d'un rayonnement et lesdits moyens d'émission d'un rayonnement comprennent une multiplicité d'éléments de réception (10) et d'émission (11) d'un rayonnement dont au moins certains d'entre eux sont situés sur un ou plusieurs bords latéraux du dispositif de telle sorte que le rayonnement peut être émis latéralement le long d'une rangée de tels dispositifs lorsqu'ils sont tenus dans une position verticale pour être utilisés comme microphones.
4. Dispositif selon la revendication 3, comprenant en outre lesdits éléments d'émission et/ou de réception le long d'un bord frontal du dispositif, lorsqu'il est au repos.
5. Système d'interrogation d'une assistance comprenant une multiplicité de dispositifs selon l'une quelconque des revendications 1 à 4 et un émetteur-récepteur (A, figure 1) agencé pour interroger lesdits dispositifs en émettant pour chaque dispositif un signal modulé en impulsion contenant son adresse unique et en stockant le signal renvoyé par chaque dispositif respectif, l'agencement étant tel que ladite multiplicité de dispositifs sont disposés dans une zone donnée pour procurer une multiplicité de trajets de propagation du rayonnement en visibilité directe en provenance dudit émetteur-récepteur (A) par l'intermédiaire d'une multiplicité desdits dispositifs agissant en tant que répéteurs jusqu'à certains autres desdits dispositifs aux frontières de ladite zone et que le trajet de propagation le plus long et le temps de réponse de chaque dispositif lorsqu'il agit en tant que répéteur sont tels que tous les répéteurs dans ledit trajet le plus long auront répondu à une impulsion donnée en provenance dudit émetteur-récepteur à l'intérieur de ladite période de temps prédéterminée pendant laquelle les moyens de réception sont mis au repos.

A




FIGURE 1




FIGURE 2




FIGURE 3




FIGURE 4